

NEC Standard Electrical Load Calculation for Single Family Dwellings

(Only for Service Ratings of 120/240V, 225 Amps Max)

Owner: _____ Location: _____

Total Floor Area of Dwelling (NEC 220.12) _____ SQFT.

Factor	Quantity	Volt Amperes (VA)
"General Lighting"		
1. General Lighting (SQFT X 3 VA/SQ FT (Table 220.12))	3 X sqft.	
2. Small Appliance Circuits (1500 VA per circuit) (NEC 220.52(A)) (minimum 2)	1500 X	
3. Laundry Circuit (1500 VA per circuit) (NEC 220.52(B))	1500 X	
4. Total General Lighting Load (Add lines 1, 2 & 3):		
5. First 3000 VA @ 100%:		3000
6. Total General Lighting Load – 3000 = _____ @ 35%= _____		
7. Net General Lighting Load (Per NEC 220.42) (Add lines 5 & 6):		
*Fixed Appliances(if insufficient space, use back):		
	YES	NO
• Garbage Disposal		
• Bathroom Fan		
• Microwave		
• Dishwasher		
• Other:		
• Other:		
Total		
8. 3 or less Appliances, Total Appliance VA; 4 or more Appliances, 75% of Total Appliance VA (NEC 220.53):		
*Other Loads (including motors, EV charger(s), etc.)		
	YES	NO
9. Electric Range (8000VA or Nameplate)**		
10. HVAC		
11. Electric Oven		
12. Electric Dryer (5000 VA minimum)**		
13. Electric Vehicle Charger	✓	
14. Other:		
15. Other:		
16. 25% of largest motor (NEC 430.24)		
Total Service Load Volt-Amperes (VA) (Add lines 7, 8 & 9 thru 16) =		
Total Service Load Volt-Amperes / 240-volts = Amperes		
***Service Rating (Amperes)=		

* For every "YES" answer, indicate VA rating of equipment

** Nameplate rating must be used if larger

*** Service Rating shall be greater than or equal to the Service load

As a covered entity under Title II of the Americans with Disabilities Act, the City of Los Angeles does not discriminate on the basis of disability and, upon request will provide reasonable accommodation to ensure equal access to its programs, services and activities.